

CA TLMS Tape Management 12.6
CA RS 1512 Service List

Release	Service	Description	Type
12.6	RO86015	MEDIA9 TAPES REJECTED IN ERROR W/CAT9062E WITH RO70798	*HIP/PRP*
The CA RS 1512 service count for this release is 1			

CA TLMS Tape Management
CA RS 1512 Service List for CATLC60

FMID	Service	Description	Type
CATLC60	RO86015	MEDIA9 TAPES REJECTED IN ERROR W/CAT9062E WITH RO70798	*HIP/PRP*
The CA RS 1512 service count for this FMID is 1			

CA TLMS Tape Management 12.6
CA RS 1512 - PTF RO86015 Details

Release	Service	Details
12.6	RO86015	<p>RO86015 M.C.S. ENTRIES = ++PTF (RO86015)</p> <p>MEDIA9 TAPES REJECTED IN ERROR W/CAT9062E WITH RO70798</p> <p>PROBLEM DESCRIPTION: MEDIA9 - IBM Extended Tape Cartridges are being rejected in error even though they are eligible to be used for output.</p> <p>SYMPTOMS: The following messages are issued, followed by a 713-04 ABEND. CAT9040I vvvvvv ON uuuu REJECTED BY CA TLMS CAT9062E MIXING WORM AND R/W VOLUMES. IEC148I 713-04,IFG0196N or IEC147I 613-40,IFG0194K.</p> <p>IMPACT: All OPEN output for MEDIA9 tapes are rejected.</p> <p>CIRCUMVENTION: None.</p> <p>PRODUCT(S) AFFECTED: CA TLMS MVS Tape Management Release 12.6</p> <p>Related Problem: TLMS 944</p> <p>Copyright (C) 2015 CA. All rights reserved. R00015-ATL126-SP1</p> <p>DESC(MEDIA9 TAPES REJECTED IN ERROR W/CAT9062E WITH RO70798). ++VER (Z038) FMID (CATLC60) PRE (RO28791 RO44766 RO47472 RO70798 RO80312 RO83793) SUP (AR70798 RO30277 RO35874 TR85542 TR86015) ++HOLD (RO86015) SYSTEM FMID(CATLC60) REASON (ACTION) DATE (15314) COMMENT (</p> <pre> +-----+ CA TLMS MVS Tape Management Release 12.6 +-----+ SEQUENCE After Apply +-----+ PURPOSE +-----+ With RO70798, tapes created on MEDIA9 cartirdges may have been marked as virtual WORM (DEN=VWRM) in the VMF. These tape volumes must be reset to a non-WORM density to prevent rejecting of the true MEDIA9 tapes. The following steps will reset the volumes with DEN=VWRM and no "write mount count". These are volumes marked as WORMs but are not real WORMs. The density will be set to DEN=3590 which is known to TLMS with and without RO86015. RO86015 will mark all MEDIA9 tapes as DEN=MED9. +-----+ USERS AFFECTED CA TLMS system programmer. +-----+ KNOWLEDGE REQUIRED CA TLMS adminstration or system programmer. +-----+ ACCESS REQUIRED CA TLMS adminstration or system programmer. +-----+ </pre>

CA TLMS Tape Management 12.6
CA RS 1512 - PTF RO86015 Details

Release	Service	Details
		<pre> ***** * STEPS TO PERFORM * ***** I. Allocate your.upv.file for 'UPV' statements. This file will hold 'UPV' statements created by the CATEARL job. RECFM=FB,LRECL=80,BLKSIZE=3120,SPACE=(CYL,(5,5)) II. Run CATEARL job to create 'UPV' statements. This will create updates for tapes marked as VWRM in error. //STEP1 CATEARL,OUTFILE=your.upv.file //CATECOGO.SYSIN DD * COPY TLESAMP1 // III. Run CATINQR job to update the VMF. This will reset the tape to a non-WORM. //STEP1 CATINQR //CAIIPT DD DSN=your.upv.file,DISP=SHR). ++HOLD (RO86015) SYSTEM FMID(CATLC60) REASON (DYNACT) DATE (15314) COMMENT (+-----+ CA TLMS MVS Tape Management Release 12.6 +-----+ SEQUENCE AFTER APPLY +-----+ PURPOSE TO ACTIVATE THE CHANGE WITHOUT AN IPL. +-----+ USERS ALL USERS. AFFECTED +-----+ KNOWLEDGE HOW TO MODIFY AND SUBMIT THE CAIRIM PROCESS. REQUIRED +-----+ ACCESS ABILITY TO SUBMIT CAIRIM WITH THE MODIFIED CONTROL REQUIRED STATEMENTS. +-----+ ***** * STEPS TO PERFORM * ***** MODIFY THE CAIRIM CONTROL STATEMENTS AS FOLLOWS; PRODUCT(CA-TLMS/MVS) VERSION(TLC6) INIT(TLC6INIT) - PARM(REINIT,LPA=TLMSOSMM,OSI=REINIT) LOADLIB(YOUR 12.6 CTAPLINK) PRODUCT(CA-TLMS/MVS) VERSION(TLC6) INIT(TLC6INIT) - PARM(REINIT,LPA=TLMSMODV) LOADLIB(YOUR 12.6 CTAPLINK) STOP AND RESTART THE CTS ADDRESS SPACE.). </pre>